

# SMART METER

## SM-S SERIES

Applicable to **LINE SPEED** or **RPM** or **LOAD RATE** display.

### FEATURES:

- Five-digit display and 3 LED indicators
- Accuracy : +/- 0.005 full scale (A/D10BIT)
- Programmable dot point and ratio
- 3 types of input interfaces for applications
- Parameter data stored in EEPROM
- Two comparison parameters for output control
- Provide selectable gear ratio : HI/MID/LO in Mode S0 and S1
- Slim body and light weight design
- Suitable for installing on operation panel



### SM-S SERIES SPECIFICATION :

COMMON SPEC.	POWER SUPPLY	POWER COM.	OPERATION TEMP.	RELATIVE HUMIDITY	VIBRATION X.Y.Z DIR.	NET WEIGHT	DISPLAY RANGE
	DC24V	3W	0-50°C	85%	0.5G	60g	0-65535

MODEL	REFLASH TIME	RANGE	UNIT	PARAMETER					
				P0	P1	P2	P3	P4	P5
SM-S-0	0.2SEC	0-10V	10V/1023	1-9999	1-9999	1-9999	1-9999	0-9999	0-9999
SM-S-1	1 SEC	1KHz	Hz	1-9999	1-9999	1-9999	1-9999	0-9999	0-9999
SM-S-2	1 CYCLE	3-3000RPM	RPM	1-9999	1-9999	None	None	0-9999	0-9999

### PARAMETER SETTING:

- Entering parameter setting mode: Press ▼ & ■ button about 6 seconds then into parameter mode. Press ■ button to quit parameter mode.
- Press ▲ or ▼ button to change and set parameter setting value.
- Press ● button to select parameter. Set item LED P0-P7 as shown followings.



**FUTURE LIFE TECHNOLOGY CO., LTD**

TEL: 886-2-82275339 FAX: 886-2-82275572

E-mail: amaker@ms24.hinet.net URL: <http://www.futuremate.com>